



Slapback Delay

The Slapback Delay is a dual PT2399 based delay pedal. Each side of the pedal is a separate delay circuit. This enables the user to use either one of the delays or engaging both giving the user a lush chorus like sound coming from the two-stacked delays. True bypass and full of tones the Slapback Delivers around 700ms of delay per section.

Layout and overview of the Slapback Delay

As you can see there are 2 separate sections to the pedal the controls starting from the left to right are as follows;

Level: Controls the level of the delay not the overall level.

Delay: Controls the delay time of the section.

Repeats: Controls the number of repeats on the delay. Turning it fully clockwise will cause runaway repeats.

Oscillate Toggle: This operates which side of the pedal will self oscillate when the middle foot switch is pressed.

Left Lower foot Switch: Turns section two of the pedal on/off.

Middle Foot Switch: Controls the oscillation or runaway repeats.

Lower Right Foot Switch: Turns section one of the pedal on/off.

DC Power Jack: The pedal operates on a 2.1mm center negative regulated power supply at 9 volts DC. Do not try to power your pedal at a higher voltage. There is no battery connection for the pedal. It operates off of power supply only.

Input and Output Jacks: These are located on the top of the pedal. When looking down on the pedal the input is on the far right and the output is on the far left.

Switching Jacks: Located on the top of the pedal. When using these to separate the separate sections of the pedal the input for section one is on the far right looking down on the pedal. The output for section one is to the immediate left of the input for section one. The input for section two is to the immediate left of the power jack. The output for section two is to the immediate left of the section two input. This enables the user to split the pedal into two separate pedals.

Your pedal operates on a 9vdc 2.1mm center negative power supply. There is no battery connection. Use high quality electronics grade cleaners and lubricants for the occasional cleaning of pedal components. If you have any other questions or concerns please visit the FAQ page at www.wilsoneffects.com or email me at wilsoneffects@wilsoneffects.com. Your new pedal is covered by a one-year warranty on parts and labor. This warranty excludes friction-based components such as potentiometers and switches.

